



Mobile phone jammer

MGT-09

CDMA / GSM / DCS / PHS / UMTS



MAGNUM TELECOM
 1, rue du Lavoir
 38590 St Etienne de St Geoirs
 France

Tél : + 33 476 31 34 92
 GSM : + 33 607 69 11 86
info@magnumtelecom.com

APPLICATIONS

Continuous mobile phone jamming

Restricted areas

Conference rooms

Exam rooms

Church, temple, mosque

Theaters

Concert Hall

Cinemas

SPECIFICATIONS

- Output power 10 or 30 watts (depending on model)
- Outdoor or indoor installation
- Range diameter 30 - 45 or 50 - 60meters
- 7 frequency bands jammed:
- IDEN, CDMA800, GSM, DCS, CDMA1900, PHS, 3G
- Working without time limit

Internal antennas, 5dBi gain.

Continuous jamming
 Does not interfere with other radio communication devices
 (ex : Talkie walky)
 Easy installation – wall or mast mounted
 Remote control provided

CHARACTERISTICS

7 Bands	Frequency bands jammed
IDEN - CDMA	850 -895 MHz
GSM	925 -965 MHz
DCS – CDMA1900 - PHS	1 800 -1 990 MHz
3G	2 110 -2 170MHz
Frequency accuracy	+/-20kHz
Range	30 to 60 meters @ -75dBm 80 meters in open space
Output power	10 or 30 watts
Power supply	AC adapter : Input : AC 220V / output : DC 12V, 3A

PRODUCT INFORMATION

Dimensions W x H x P	285 x 270 x 95 mm
Weight	3 kg
Operating temperature	-10°/ +60°C
Warranty	1 year