



Mobile phone jammer

MGT- P1

GSM / DCS / 3G



MAGNUM TELECOM
 1, rue du Lavoir
 38590 St Etienne de St Geoirs
 France

Tél : + 33 476 31 34 92
 GSM : + 33 607 69 11 86
info@magnumtelecom.com

APPLICATIONS

Continuous mobile phone jamming

- Restricted areas
- Conference rooms
- Exam rooms
- Chuch, temple, mosque
- Theaters
- Concert Hall
- Cinemas

SPECIFICATIONS

- Output power 450 mWatts
- Range diameter 4 to 8 meters
- Operating time 2 to 3 hours
- 3 frequency bands (GSM, DCS, 3G)

External antennas.
 Continuous jamming
 Does not interfere with other radio communication devices (ex : DECT phones, talkie walkie)
 Easy installation – wall mounted
 Cigar lighter adapter provided
 Small dimensions

CHARACTERISTICS

| | |
|--------------------|---|
| | Frequency bands jammed |
| GSM | 925 -960 MHz |
| DCS | 1 805 -1 880 MHz |
| UMTS, 3G | 2 110 -2 170MHz |
| Frequency accuracy | +/-20kHz |
| Range | 4 to 8 meters @ -75dBm 10 meters in open space |
| Output power | 450 mWatts |
| Power supply | AC adapter : Input : AC 220V / output : DC 5V, 3A |

PRODUCT INFORMATION

| | |
|-----------------------|------------------------------|
| Dimensions W x H x P | 100 x 18 x 42 mm (aluminium) |
| Weight | 150 g |
| Operating temperature | 0°/ +70°C |
| Warranty | 1 year |