



**MAGNUM TELECOM**  
 1, rue du Lavoir  
 38590 St Etienne de St Geoirs  
 France

Tél : + 33 476 31 34 92  
 GSM : + 33 607 69 11 86  
[info@magnumtelecom.com](mailto:info@magnumtelecom.com)

**APPLICATIONS**

*Continuous mobile phone jamming*

- Restricted areas
- Conference rooms
- Exam rooms
- Chuch, temple, mosque
- Theaters
- Concert Hall
- Cinemas

Mobile phone jammer

GSM / DCS / 3G

**MGT- P2**



**SPECIFICATIONS**

- Output power 900 mWatts
- Range diameter 15 to 20 meters
- Operating time 90 minutes
- frequency bands (GSM, DCS, DECT, 3G)

External antennas.  
 Continuous jamming  
 Does not interfere with other  
 radio communication devices  
 (ex : talkie walkie)  
 Cigar lighter adapter provided  
 Small dimensions

**CHARACTERISTICS**

	Frequency bands jammed
GSM	925 -960 MHz
DCS	1 805 -1 880 MHz
UMTS, 3G	2 110 -2 170MHz
Frequency accuracy	+/-20kHz
Range	15 to 20 meters @ -75dBm 25 meters in open space
Output power	900 mWatts
Power supply	AC adapter : Input : AC 220V / output : DC 12V, 4A

**PRODUCT INFORMATION**

Dimensions W x H x P	62 x 110 x 30 mm (aluminium)
Weight	300 g
Operating temperature	0° / +80°C
Warranty	1 year